

SCANMEG

Type TL



Transverse profile scanner (extended range)

- Simple alignment
- Watertight casing
- Single power supply
- Up to 1500 scans/sec.
- Daisy-Chain interconnection
- LED detection status for each cell
- Maximum of 32 sections per system

<u>Model</u>	
TL	
TL2	

<u>Section</u>	
4 ft	120 cm
2 ft	60 cm

<u>Maximum length</u>	
128 ft	39 m
64 ft	20 m

0.2 mm

Accuracy

0.008 in.

The Type TL are the ideal scanners for transverse scanning of logs and stems or, inside sawmills, for log carriage scanner deck or board optimizer or for any other applications requiring fast and accurate profile measurement.

According to the type of scanner chosen; with this light-curtain scanner profiles are taken at every 2.5 cm (1 in.) or at every 5 cm (2 in.) along the length of the object.

Model

TL
TL2

Section

TL: 4 ft 120 cm
TL2: 2 ft 60 cm

Maximum length

TL: 128 ft 39 m
TL2: 64 ft 20 m

Sensors spacing

TL: 1 in. 2.5 cm
TL2: 2 in. 5 cm

Power supply

15 to 24 Volts DC

Operating Temperature

Min.: -40°F -40°C
Max.: 120°F 50°C

Maximum consumption

TL : 400 mA per section
TL2 : 200 mA per section

Detection range

TL : 12 ft 4 m
TL2 : 6 ft 2 m

Maximum Scan rate

(scans/sec.)

TL: 1000
TL2: 1500

Output Interface

Serial link
RS-422

TL Model

Model TL measures profile and length of an object passing in its field of view. Each individual sensor, within the scanner, scans at a rate of 1000 scans/sec., thus a profile of a great accuracy is achieved. The object's length is also found with an accuracy of 2.5 cm (1 in.). The TL scanner can also be shipped with sensors cells (option OPT2) spaced at 5 cm (2 in.).

TL2 Model

This model is a simplified version of model TL. It has less sensors thus making it a faster scanner but with less accuracy on the length 5 cm (2 in.). The TL2 scanner scans at 1500 scans per second.

Module DEC-S4



The DEC-S4 module is used with this scanner to divide or multiply an encoder signal to obtain an ideal pulse speed for a given application environment. Also this module multiplexes an encoder signal into 4 separate outputs with different or identical voltage to be used simultaneously by several controllers.



3517 Boul. Grande Allee,
Boisbriand, QC
Canada, J7H 1H5

Tel.: (450) 419-4555
Fax: (450) 419-4542
Email: sales@scanmeg.com
Web: www.scanmeg.com

The Ultimate Sensor Company

North America *(Western Representative)*

John Wilby
10972 Swan Crescent
Surrey, BC, V3R 5B6
Tel.: 604-582-2157
Fax: 604-582-2105
Cell.: 604-290-6595
Email: jlwilby@scanmeg.com

Europe

82 Route de Séchex
F-74200 ANTHY-SUR-LEMAN
France
Tel. / Fax: +33 (0)4 50 17 25 33
Cell: +33 (0)6 31 54 38 06
Email: europe@scanmeg.com

Japan

532 Ohyanagi Minami Shimada-City
Shizuoka-Prefecture
Japan, 427-0102
Tel.: +81-547-38-3211
Fax: +81-547-38-2122
Email: info@hirotacorp.jp